



GB04/4572



INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

REC'D 07 JAN 2005

WIPO


PCT

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.



Signed

Dated


P. Mahoney
20 December 2004

BEST AVAILABLE COPY

**PRIORITY
DOCUMENT**

SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Patents Form 1/77
Patents Act 1977
(Rule 16)



08MAR04 E878760-1 D02917
P01/7700 0.00-0405026.6 ACCOUNT CHA

Request for grant of a patent

The Patent Office
Cardiff Road
Newport
South Wales NP10 8QQ

1. Your reference
5484202/JAC
2. Patent Application Number
05 MAR 2004 0405026.6
3. Full name, address and postcode of the or of each applicant (*underline all surnames*)

Innovision Research & Technology PLC
Ash Court
23 Rose Street
Wokingham
Berkshire
RG40 1XS

Patents ADP number (*if known*) 08144784001

If the applicant is a corporate body, give the country/state of its incorporation Country: England
State:

4. Title of the invention
DUAL MODE READER / TAG ARCHITECTURE

5. Name of agent Beresford & Co
"Address for Service" in the United Kingdom 16 High Holborn
to which all correspondence should be sent London WC1V 6BX

Patents ADP number 00001826001
electronic Intellectual Property
Suite 308, The Foundry
156 BLACKFRIARS ROAD
LONDON SE1 2EN

6. Priority: Complete this section if you are declaring priority from one or more earlier patent applications filed in the last 12 months.

Country Priority application number Date of filing

Patents Form 1/77

7. Divisionals, etc: Complete this section only if this application is a divisional application or resulted from an entitlement dispute.

Number of earlier application

Date of filing

8. Is a Patents Form 7/77 (Statement of inventorship and of right to grant of a patent) required in support of this request?

YES

9. Enter the number of sheets for any of the following items you are filing with this form.

Continuation sheets of this form

Description

3 /

Claim(s)

1 /

Abstract

0

Drawing(s)

2 + 2 jmc

10. If you are also filing any of the following, state how many against each item.

Priority documents

NO

Translations of priority documents

NO

Statement of inventorship and
right to grant of a patent (*Patents form 7/77*) 1 + 1 COPY J

Request for preliminary examination
and search (*Patents Form 9/77*)

NO

Request for Substantive Examination
(*Patents Form 10/77*)

NO

Any other documents
(please specify)

NO

11. I/We request the grant of a patent on the basis of this application

Signature

Beresford

BERESFORD & Co

Date 5 March 2004

12. Name and daytime telephone number of
person to contact in the United Kingdom

Jane Clark

Tel: 020 7831 2290

Dual Mode Reader / Tag Architecture

DUPLICATE

1 Background

The growth and diversity of RFID applications and the use of near field communication ("NFC") systems is progressing at an exponential rate. The existing RFID system concepts, based on isolated Reader and Tag functionality, do not necessarily provide the optimum system level solution for an ever-increasing diversity of application areas. Many of these emerging application areas may require each element within the RFID or NFC system to possess dual mode Reader / Tag functionality or dual activity rather than one passive and one active component in any system, analogous to the transceiver functionality that exists within radio transmission equipment today.

Several technical problems need to be addressed to realise a dual mode Reader / Tag functionality or NFC systems in which both reader and tag functionality exist to the same level. Firstly, for a dual antenna solution, close proximity of the antennas will result in interference between the antennas. This effect is especially acute for proximity or vicinity coupled systems where the coupling mechanism is magnetic. The solution to this problem would involve either positioning the antennas at mutual magnetic nulls, or including an enable/disable function for the system antenna. Both of these solutions are likely to result in increased complexity, cost and size of the dual mode solution. Secondly, for a single antenna solution, the inherently different properties of the antennas used for reader and/or tag functionality could result in range reduction due to insufficient modulation depth depending on the design of the antenna. The following sections outline the IRT proposed solution for a single antenna dual mode Reader / Tag functionality or NFC system. The IRT proposed solution achieves maximum range performance, with minimal increase in circuit complexity, without a significant size or cost penalty compared to a conventional single mode Reader / Tag system or NFC system. Additional advantages of the suggested architecture are reduced silicon area and reduced power consumption.

2 Proposed Solution Operational Overview

Example 1

An example proposed solution is illustrated in Figure 1. In "Reader" or active mode the resonant antenna (or antennae) is driven with a carrier excitation signal as per a conventional Reader configuration. In "Tag" mode or passive mode (which could be a default condition) a phase locked loop (PLL) is used to provide a local phase-coherent oscillator. The PLL is a second order loop comprising a phase detector, loop filter and VCO. By incorporating a track and hold function between the loop filter and VCO, it is possible to hold the local phase-coherent oscillator signal in the absence of input signal to the phase detector (subject to voltage drift in the track and hold function when in the "hold" mode). A feature of the present invention is to integrate the track and hold with the loop filter as exemplified in Figure 2. If the track and hold and loop filter functions are truly separate, then the output of the loop filter can saturate at either extreme of its range when the negative feedback loop is broken by placing the track and

hold into hold mode. This can cause an increase in loop lock-in time due to the inherent loop filter (lowpass like) response when the negative feedback loop is re-established by placing the track and hold in track mode to re-synchronise with an incoming signal. The loop filter of Figure 2 is placed into hold mode by opening the switch between the phase detector and the input to the filter proper. When open, the filter can be approximated as a floating integrator whose capacitive element will hold the last DC voltage applied to it (neglecting fixed error sources such as leakage currents and offset voltages). This function can be better described as a "filter and hold function". To function correctly, it is essential that the filter is commanded into hold mode only when the loop has completely stabilized and the output of the phase detector is no longer changing.

When phase lock is achieved (as indicated by a lock detect function within the PLL phase detector) the micro-controller is alerted and asserts a signal which commands the track and hold to enter hold mode thereby holding the VCO control voltage within the PLL. The PLL loop is now broken and the VCO output is a phase coherent replica of the reader carrier signal. Clearly, the phase-coherence will slowly degrade over time due to the natural droop of the track-and-hold function. However, the technique does not require perfect phase coherence to operate and in any case the time for which the PLL will be 'free running' is small compared to the droop rate of the envisaged track-and-hold. (Degrading phase coherence will cause a corresponding and steady reduction in modulation depth as seen by the reader.)

The phase-coherent local reference is modulated by the emulated tag data pattern and modulates (either constructively or destructively) the current in the emulated tag antenna. This is reflected back to the external reader through mutual inductive coupling and thereby appears as modulated data at the reader. A key variable in this architecture is the drive level applied to the emulated tag antenna. This level should be dynamically adjustable according to the signal level received from the external reader to avoid the possibility of overloading the external reader receiver input amplifier. We accommodate this by utilising an amplitude levelling-loop referenced from the received carrier amplitude detector block. This loop serves to keep the phase inverted drive level at some optimum point which depends on system characteristics.

An additional feature of this approach is the utilisation of the PLL sub-system as part of a synchronous demodulator. When in Reader mode the received modulated carrier from a remote reader (which will not, by definition, be phase-coherent with the local carrier oscillator) can be used to drive the PLL and thereby obtain a phase-coherent local oscillator which is used in conjunction with a synchronous detection of the incoming modulated carrier.

Example 2

Using the dual mode Reader / Tag architecture or NFC system in Tag or passive mode the power detector within the receiving circuitry captures a sampled measurement of the received signal strength. This information can be used, within the controller and AGC, in conjunction with other calibration or predictive data if required, to set and control the output modulation depth, with the modulator and driver, to a desired value using an AGC algorithm. This desired value can take several forms, examples of which are listed, but not limited to, the following cases.

- To provide a constant, e.g., 10% or 100% modulation depth, as perceived by a separate external Reader or NFC system, independent of received signal strength,

i.e. distance between the separate Reader or NFC system and the dual mode Reader / Tag or NFC system.

- To provide a power limiting capability enabling active overload protection for separate external Readers or NFC systems, for example, when the external Reader or NFC System and the Dual mode Reader / Tag or first NFC system are in extremely close proximity.

3 Benefits of Proposed Solution

The proposed solution has a major benefit over conventional passive Tag operation and for the evolution of NFC systems. With a conventional passive Tag the modulation depth is limited by the energy of the incoming signal. With the proposed solution this limitation is removed, as the modulation depth is dependent on the energy that can be generated by the driver stage, which is independent of any external signals or circuitry.

The example proposed solution may also be used with other forms of antenna or multiple antennas, and other coupling mechanisms, such as far field electromagnetic, acoustic, optical etc.

Other examples of the proposed solution would include but are not limited to,

- Injection Locking receiving circuitry
- Parametric amplifying receiving circuitry
- Delay lock loop receiving circuitry

4 Claims

1. A Reader or NFC architecture that can emulate TAG functionality.
2. A dual mode Reader / Tag architecture or NFC architecture using a phase locking technique for the Tag or passive mode of operation.
3. A dual mode Reader / Tag architecture or NFC system where the functionality modulation depth is independent of the energy of the incoming or separate Reader or NFC signal.
4. A dual mode Reader / Tag architecture or NFC architecture where the functionality modulation depth that is read by an external reader or NFC system can be set to a predefined value.
5. A dual mode Reader / Tag architecture where the functionality modulation depth hat is read by an external reader or NFC system can be set to provide overload protection for the external Reader or NFC system.
6. A reader or NFC system capable of providing synchronous demodulation of a received signal consisting a local phase locked loop said phase locked loop phase-synchronising with the incoming signal.

Figure 1: IRT Dual Mode Reader / Tag Solution or NFC System





Figure 2: Composite Track & Hold and Loop Filter



PCT/GB2004/004572



**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record.**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☒ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☒ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☒ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER: _____**

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.